



Main

Relay application	Transformer
Range of product	Sepam series 40
Device short name	T40
Control and monitoring type	Latching/acknowledgement ANSI code: 86 Logic discrimination ANSI code: 68 (option) Switching of groups of settings Annunciation ANSI code: 30 Circuit breaker/contactors control ANSI code: 94/69 Logic equation editor 100 operators
Metering type	Phase current I1, I2, I3 RMS, residual current I0 Demand current I1, I2, I3, peak demand current IM1, IM2, IM3 Temperature (option) Voltage U21, U32, U13, V1, V2, V3, residual voltage V0 Frequency Positive sequence voltage Vd/rotation direction-negative sequence voltage Vi Active, reactive, apparent power P,Q,S-peak demand power PM, QM, power factor Calculated active and reactive energy (+/- W.h, +/- VAR.h) Active and reactive energy by pulse counting (+/- W.h, +/- VAR.h) (option)
Network and machine diagnosis type	Unbalance ratio/negative sequence current Ii Disturbance recording Thermal capacity used Remaining operating time before overload tripping Waiting time after overload tripping Running hours counter/operating time Tripping context Phase displacement
Switchgear diagnosis type	Cumulative breaking current Trip circuit supervision (option) Number of operations, operating time charging time (option) CT/VT supervision ANSI code: 60FL

Complementary

Type of measurement	Current Energy Power (P,Q) Frequency Temperature Voltage Peak demand power
---------------------	----------------------------------------------------------------------------------------------

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Power factor

Protection type	Thermal overload protection ANSI code: 49RMS Thermostat / buchholz ANSI code: 26/63 (option) Neutral voltage displacement ANSI code: 59N Breaker failure ANSI code: 50BF Undervoltage protection ANSI code: 27/27S Overvoltage protection ANSI code: 59 Temperature monitoring (8 or 16 RTDs) ANSI code: 38/49T (option) Phase overcurrent ANSI code: 50/51 Earth fault/sensitive earth fault ANSI code: 50N/51N Earth fault/sensitive earth fault ANSI code: 50G/51G Negative sequence/unbalance ANSI code: 46 Negative sequence overvoltage ANSI code: 47 Overfrequency ANSI code: 81H Underfrequency ANSI code: 81L
Communication port protocol	Measurement readout (option) : Modbus Remote indication and time tagging of events (option) : Modbus Remote control orders (option) : Modbus Remote protection setting (option) : Modbus Transfer of disturbance recording data (option) : Modbus
Input output max capacity	10 inputs + 8 outputs
Communication compatibility	Modbus RTU Modbus TCP/IP IEC 60870-5-103 IEC 61850 DNP3
User machine interface type	Without Remote Advanced

Packing Units

Package 1 Weight	0.001 kg
Package 1 Height	0.010 dm
Package 1 width	0.010 dm
Package 1 Length	0.020 dm

Offer Sustainability

EU RoHS Directive	Not applicable, out of EU RoHS legal scope
-------------------	--------------------------------------------